

TECHNICAL HANDOUT

CHANGING THE DATE AND TIME ON THE

Interconnect 3000 Console

*To determine if the system clock is PC driven, on the Switchboard press F10, C, O, Enter
The second entry in this form is "Auto Clock Set"
If this is set to YES, then these instructions are appropriate.
Press ESC repeatedly to exit programming.*

FROM THE MAIN CONSOLE (Switchboard)

1. Press **F 10** (menu)
2. Select **set authorisation level** (using up and down arrow keys)
3. Press **ENTER**
4. Select **operator** (using up and down arrow keys)
5. Press **ENTER**
6. Enter password (**LEVEL 1**) then press **ENTER**
7. Press **ESCAPE** twice
8. Press **F 10**
9. Go to **CONFIGURATION** (using up and down arrow keys)
10. Press **ENTER**
11. Go to **SYSTEM** (using up and down arrow keys)
12. Press **ENTER** then press **F9** to edit
13. Press the **DOWN ARROW**, until you get to **Time**
14. Press the **RIGHT ARROW** until cursor is passed end of date
15. Press the **BACK SPACE** to delete
16. Enter correct time (the format should be **HH:MM:SS**)
17. **ARROW DOWN** to move off of time field
18. **ARROW DOWN** to Date if **required**, otherwise go to 23
19. Press the **RIGHT ARROW** until cursor is passed end of date
20. Press the **BACK SPACE** to delete
21. Change the date (**the format should be; 12-10-00**) using the Numerical keys along the top of keyboard (above letters)
22. **ARROW DOWN** to move off of date field
23. Press **ESCAPE** repeatedly until you are back to main screen

If you have any problems with the above, please call our

Support Department on 08450 34 55 66