



TECHNICAL HANDOUT

CHANGING THE DATE AND TIME ON THE

Interconnect 3000 Console PC

*To determine if the system clock is PC driven, on the Switchboard press F10, C, O, Enter
The second entry in this form is "Auto Clock Set"
If this is set to YES, then these instructions are appropriate.
Press ESC repeatedly to exit programming.*

FROM THE MAIN CONSOLE (Switchboard)

1. Press **F 10** (menu)
2. Select **set authorisation level** (using up and down arrows)
3. Press **ENTER**
4. Select **installer** (using up and down arrow keys)
5. Press **ENTER**
6. Enter password (**D T T C T P**)
7. Press **ENTER**
8. Press **ESCAPE**
9. Go to **EXIT TO DOS** (using up and down arrow keys)
10. Press **ENTER**
11. Type **Y**
12. Press **ENTER**
13. You will now be at a black DOS screen
14. Type **TIME (hh:mm:ss)**
15. Enter new time
16. Press **ENTER**
17. **If required**, type **DATE - otherwise go to step 22**
18. Enter correct date (**mm-dd-yy**)
19. Press **ENTER**
20. Type **CONSOLE**
21. The console will now start up (allow a minute or so to load)

If you have any problems with the above, please call our

Support Department on 08450 34 55 66